

## FUSE LINK SMALL BENT MALE TERMINAL 32V





Small Body Part Number	Ampere Rating	Body Colour	
SBF030	30A	Pink	■
SBF040	40A	Green	■
SBF050	50A	Red	■
SBF060	60A	Yellow	■
SBF070	70A	Brown	■
SBF080	80A	Black	■
SBF100	100A	Blue	■
SBF120	120A	White	□
SBF140	140A	Maroon	■

**Voltage:** 32VDC **I.R.:** 1000A at 32VDC


**Characteristic:** Slow Acting

**Pack Size:** 1, 10, 100

**Approvals:** ISO 8820 / JASO D612 RoHS



36mm Fixing Centers



Dimensions in MM

## FUSE LINK LARGE BENT MALE TERMINAL 32V




Large Body Part Number	Ampere Rating	Body Colour	
LBF030	30A	Pink	■
LBF040	40A	Green	■
LBF050	50A	Red	■
LBF060	60A	Yellow	■
LBF070	70A	Brown	■
LBF080	80A	Black	■
LBF100	100A	Blue	■
LBF120	120A	White	□
LBF140	140A	Maroon	■

**Voltage:** 32VDC **I.R.:** 1000A at 32VDC


**Characteristic:** Slow Acting

**Pack Size:** 1, 10, 100

**Approvals:** ISO 8820 / JASO D612 RoHS



49mm Fixing Centers



Dimensions in MM

## FUSE LINK STRAIGHT MALE TERMINAL 32V




Bolt Hole Terminal Part Number	Cut Out Terminal Part Number	Ampere Rating	Body Colour	
BTF030	BTCF030	30A	Pink	■
BTF040	BTCF040	40A	Green	■
BTF050	BTCF050	50A	Red	■
BTF060	BTCF060	60A	Yellow	■
BTF070	BTCF070	70A	Brown	■
BTF080	BTCF080	80A	Black	■
BTF100	BTCF100	100A	Blue	■
BTF120	BTCF120	120A	White	□
BTF140	BTCF140	140A	Maroon	■

**Voltage:** 32VDC **I.R.:** 1000A at 32VDC

**Characteristic:** Slow Acting


**Pack Size:** 1, 5, 10, 100

**Approvals:** ISO 8820 / JASO D612 RoHS



Bolt Hole Type

**NEW**



Dimensions in MM



Cut Out Type